

# MP250UB Mini Mixer Amplifier



## *Features*

- Built-in Bluetooth, radio and USB function.
- 2 MIC IN, 2 EMC IN, 2 LINE IN, 1 LINE OUT.
- 100V or 70V constant voltage output, 4Ω~16 Ω constant resistance output.
- Support IR remote control.
- With priority function, priority is EMC/MIC1>AUX1/AUX2/MIC2.
- With master volume control, and individual volume control of MIC & LINE, as well as treble and bass volume control.

## *Specifications*

<b>Model</b>	MP250UB
<b>Power Supply</b>	AC110-120V / AC220~240V 50/60Hz(Select via the switch)
<b>MIC1 IN Sensitivity</b>	8mV±10%
<b>MIC2 IN Sensitivity</b>	8mV±10%
<b>AUX1 IN Sensitivity</b>	350mV±10%
<b>AUX2 IN Sensitivity</b>	350mV±10%
<b>EMC IN Sensitivity</b>	350mV±10%
<b>MIC Frequency Response</b>	200Hz ~ 10kHz (±3dB)
<b>AUX Frequency Response</b>	100Hz ~ 16kHz (±3dB)
<b>Noise</b>	<10mV
<b>Distortion</b>	<1% 1KHz
<b>Treble Adjustment</b>	10dB (±2)
<b>Bass Adjustment</b>	10dB (±2)
<b>Rated Output Power</b>	250W
<b>Interface Output Voltage</b>	70V,100V(Constant voltage output).
<b>Machine Dimension (D×W×H)</b>	250×230×66mm
<b>Package Dimension</b>	363×292×106mm (1PC)
<b>Maximum Package Dimension</b>	610×390×240mm (4PCS)
<b>Net Weight</b>	3KG
<b>Gross Weight</b>	3.7Kg (1PC)