



# 120W 240W 500W 5 ZONES DIGITAL MIXER AMPLIFIER 100V 4Ω

minkEZ

MA-120V5Z MA-240V5Z MA-500V5Z



Model	MA-120V5Z	MA-240V5Z	MA-500V5Z
Rated Power	120W	240W	500W
Output Level	4-16Ω/100V		
Input Sensitivity	MIC1, 2, 3, 4 Input: 5mV/600Ω unbalanced 6. 3 PHONE JACK connection terminal; AUX1, 2 Input: 350mV/10KΩ unbalanced RCA connection terminal; EMC input: 775mV/10KΩ unbalanced 6. 3 PHONE JACK connection terminals		
Output Sensitivity & Impedance	MIX OUT: 1000mV/470Ω unbalanced RCA connection terminal		
Tones	Bass: ±10dB at 100Hz Treble: ±10dB at 10KHz		
Frequency Response	80Hz~16KHz (+1dB, -3dB)		
Cross talk attenuation	≥50dB		
SNR	MIC1、2、3: 66dB ; AUX1、2: 85dB		
THD	≤0.05%(at 1KHz, 1/3 rated power)		
Indicator	Power indicator		
Cooling Mode	Air cooling		
Protection Mode	Short circuit, overload and overheating protection		
Operation Temperature	+5℃~+40℃		
Storage Temperature	-20℃~+70℃		
Relative Humidity	<95%(No condensation)		
Voltage	~240V 50Hz		
Power Consumption	160W	300W	650W
Weight	4.5Kg	5.1Kg	5.8Kg
Dimension	484×295×44mm		