



### FEATURES

- \* With the 2U chassis, high integration, modular design.
- \* When equipment shutting down and powering off, it will not affect normal broadcasting
- \* Support 8 main amplifier and 1 standby amplifier, it will automatically switch to standby amplifier when one main amplifier faulty.
- \* Real time power amplifier status detection, and with different colors for the indicators.
- \* With Ethernet interface, can be integrated with third party system, and realize the centralized supervision and distributed control.

<b>Model</b>	MCU-18
<b>Power Supply</b>	~220V/50Hz
<b>Maximum Current</b>	0.1 A
<b>Specification of Fuse</b>	50V/1A, Slow type
<b>Power Consumption</b>	15W
<b>Distortion</b>	<0.1%(Rated Output Power), 1kHz
<b>Frequency Response</b>	20Hz~20kHz
<b>Sensitivity</b>	775mV
<b>SNR</b>	>70dB
<b>Impedance</b>	10kΩ
<b>Cooling Method</b>	natural cooling
<b>Operating Temperature</b>	+5℃~+40℃
<b>Storage Temperature</b>	-20℃~+70℃
<b>Relative Temperature</b>	<95%(Without condensation)
<b>Dimension(L*W*H)</b>	484 x 88 x 447 mm
<b>Weight</b>	5Kg

